


# GMB HR168

grifo® Mini BLOCK Housing, 16 Opto Input, 8 Relay Outputs

# GMM AM644

grifo® Mini Module AT mega 644P

## TECHNICAL MANUAL



**grifo®**

ITALIAN TECHNOLOGY

Via dell' Artigiano, 8/6  
40016 San Giorgio di Piano  
(Bologna) ITALY

E-mail: [grifo@grifo.it](mailto:grifo@grifo.it)


<http://www.grifo.it>

<http://www.grifo.com>

Tel. +39 051 892.052 (r.a.) FAX: +39 051 893.661



GMB HR168+GMM AM644 Rel. 5.00 Edition 12 August 2011

 GPC®, grifo®, are trade marks of grifo®



# GMB HR168

grifo® Mini BLOCK Housing, 16 Opto Input, 8 Relay Outputs

# GMM AM644

grifo® Mini Module AT mega 644P

## TECHNICAL MANUAL

Couple between interface board of **Digital Block GMB HR168** series and **Mini Modules** with **AVR Core** with **40 pins GMMAM644**, able to manage application that involves both **Digital** and **Analog Signals** and line **Communication**.

**grifo®**

ITALIAN TECHNOLOGY

Via dell' Artigiano, 8/6  
40016 San Giorgio di Piano  
(Bologna) ITALY

E-mail: grifo@grifo.it


<http://www.grifo.it>

<http://www.grifo.com>

Tel. +39 051 892.052 (r.a.) FAX: +39 051 893.661



GMB HR168+GMM AM644 Rel. 5.00 Edition 12 August 2011

 GPC®, grifo®, are trade marks of grifo®

## DOCUMENTATION COPYRIGHT BY grifo®, ALL RIGHTS RESERVED

No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, either electronic, mechanical, magnetic, optical, chemical, manual, or otherwise, without the prior written consent of grifo®.

### IMPORTANT

Although all the information contained herein have been carefully verified, grifo® assumes no responsibility for errors that might appear in this document, or for damage to things or persons resulting from technical errors, omission and improper use of this manual and of the related software and hardware.

grifo® reserves the right to change the contents and form of this document, as well as the features and specification of its products at any time, without prior notice, to obtain always the best product.

For specific informations on the components mounted on the card, please refer to the Data Book of the builder or second sources.

### SYMBOLS DESCRIPTION

In the manual could appear the following symbols:



Attention: Generic danger




Attention: High voltage



Attention: ESD sensitive device

### Trade Marks

, GPC®, grifo® : are trade marks of grifo®.  
Other Product and Company names listed, are trade marks of their respective companies.

# GENERAL INDEX

COUPLE RESOURCES ..... 1

COUPLE CONNECTIONS ..... 1



# INDICE DELLE FIGURE

FIGURE 1: CONNECTIONI TABLE (1 OF 7) .....	2
FIGURE 2: CONNECTIONI TABLE (2 OF 7) .....	3
FIGURE 3: CONNECTIONI TABLE (3 OF 7) .....	4
FIGURE 4: CONNECTIONI TABLE (4 OF 7) .....	5
FIGURE 5: CONNECTIONI TABLE (5 OF 7) .....	6
FIGURE 6: CONNECTIONI TABLE (6 OF 7) .....	7
FIGURE 7: CONNECTIONI TABLE (7 OF 7) .....	8

## COUPLE RESOURCES

The **GMB HR168 + GMM AM644** couple has the following resources:

<b>Relay Outputs:</b>	8
<b>Optocoupled Inputs:</b>	15
<b>Optocoupled Inputs Type:</b>	NPN , PNP, Powered
<b>Multifunction Signals I/O TTL, A/D, PWM, CAN, etc.:</b>	6
<b>Analog Input (0÷Vfs, 0÷4*Vfs):</b>	1
<b>Max. Value Voltage of A/D Converter (Vfs):</b>	2,5 V o 10,0 V
<b>Serial Line in RS 232:</b>	1
<b>Serial Line in TTL:</b>	1
<b>Serial Line in RS 422:</b>	1
<b>Serial Line in RS 485:</b>	1
<b>Serial Line in Current Loop:</b>	1
<b>Serial Line in I2C BUS:</b>	YES
<b>CAN Interface:</b>	NO
<b>USB Interface:</b>	NO
<b>LITIUM Battery</b>	YES
<b>Real Time Clock:</b>	YES
<b>FRAM</b>	YES

It is important to note that the previous list shows the maximum available resources and some of these ones are not usable in the same time, as described in following figures.

## COUPLE CONNECTIONS

In the following tables are reported connections of all user available signals on **GMB HR168** related to **GMM AM644 Mini Module**. With these connections the user can manage all available resources either by hardware and by software.

When a more detailed documentation is required (connection diagrams, signals location on connectors, power supply, jumpers configuration ,software management, etc.) please, see technical manuals of the two modules contained in the couple.

In the tables are present the following abbreviations and references:

N.C. = Not Connected

N.M. = Not Mounted

\*1 = to configure according to the performed connection.

GMM HR168 Connector Pin	GMM HR168 Signal Name	GMM HR168 Configuration	ZC1 Pin	GMM AM644 Pin	GMM AM644 Configuration	GMM AM644 Signal Name	Use on GMM AM644
<b>CN1: Connector for Optocoupled Digital Inputs</b>							
CN1.1	IN1-A	-	32	32	-	PA.1	-
CN1.2	IN2-A	-	31	31	-	PA.2	-
CN1.3	IN3-A	-	25	25	-	PC.2	-
CN1.4	IN4-A	-	24	24	-	PC.3	-
CN1.5	IN5-A	-	23	23	-	PB.0	-
CN1.6	IN6-A	-	22	22	-	PB.1	-
CN1.7	IN7-A	-	21	21	-	PC.4	-
CN1.8	IN8-A	-	19	19	-	PC.5	-
CN1.9	COMUNE	-	-	-	-	-	-
<b>CN2: Connector for Optocoupled Digital Inputs</b>							
CN2.1	IN1-B	-	1	1	-	PB.4	-
CN2.2	IN2-B	-	2	2	-	PB.3	-
CN2.3	IN3-B	-	3	3	-	PB.2	-
CN2.4	IN4-B	-	4	4	-	PC.6	-
CN2.5	IN5-B	-	35	35	-	PD.4	-
CN2.6	IN6-B	-	36	36	-	PD.6	-
CN2.7	IN7-B	-	37	37	-	PD.7	-
CN2.8	IN8-B	-	38	38	-	-	-
CN2.9	COMUNE	-	-	-	-	-	-

FIGURE 1: CONNECTION TABLE (1 OF 7)



GMB HR168 Connector Pin	GMB HR168 Signal Name	GMB HR168 Configuration	ZC1 Pin	GMM AM644 Pin	GMM AM644 Configuration	GMM AM644 Signal Name	Use on GMM AM644
<b>CN3: Connector for Relays Outputs</b>							
CN3.1	OUT A1	-	29	29	-	PA.3	-
CN3.2	COMMON A	-	-	-	-	-	-
CN3.3	OUT A2	-	28	28	-	PA.4	-
CN3.4	OUT B1	-	27	27	-	PA.5	-
CN3.5	COMMON B	-	-	-	-	-	-
CN3.6	OUT B2	-	26	26	-	PA.6	-
CN3.7	OUT C1	-	14	14	-	PB.5	-
CN3.8	COMMON C	-	-	-	-	-	-
CN3.9	OUT C2	-	15	15	-	PB.6	-
<b>CN4: Connector for Relays Outputs</b>							
CN3.1	OUT D1	-	18	18	-	PB.7	-
CN3.2	COMMON D	-	-	-	-	-	-
CN3.3	OUT D2	-	16	16	-	PA.7	-

FIGURE 2: CONNECTION TABLE (2 OF 7)

GMB HR168 Connector Pin	GMB HR168 Signal Name	GMB HR168 Configuration	ZC1 Pin	GMM AM644 Pin	GMM AM644 Configuration	GMM AM644 Signal Name	Use on GMM AM644	
<b>CN6: Connector for Asynchronous Serial Line in RS 232 (1)</b>								
CN6.1	+5 Vdc	-	34	34	-	+Vdc POW	-	
CN6.2	Vopto A	-	-	-	-	-	-	
CN6.3	TX RS232	J3, J4, N.C. J6, J7, J8 in 2-3 J5, Indifferente	10	10	Jumpers J1.1 = 2-3 J1.2 = 2-3 J1.3 = 2-3	PDO , TXD RS232 , TXD TTL	-	
CN6.4	-		-	-		-	-	-
CN6.5	RX RS232		9	9		-	PD1 , RXD RS232 , RXD TTL	-
CN6.6	-		-	-		-	-	-
CN6.7	GND	-	20	20	-	GND	-	
CN6.8	Vopto B	-	-	-	-	-	-	
<b>CN6: Connector for Asynchronous Serial Line in TTL</b>								
CN6.1	+5 Vdc	-	34	34	-	+Vdc POW	-	
CN6.2	Vopto A	-	-	-	-	-	-	
CN6.3	TX TTL	J3, J4, N.C. J6, J7, J8 in 2-3 J5, Indifferente	10	10	Jumpers J1.1 = 1-2 J1.2 = 1-2 J1.3 = 1-2	PDO , TXD RS232 , TXD TTL	-	
CN6.4	-		-	-		-	-	-
CN6.5	RX TTL		9	9		-	PD1 , RXD RS232 , RXD TTL	-
CN6.6	-		-	-		-	-	-
CN6.7	GND	-	20	20	-	GND	-	
CN6.8	Vopto B	-	-	-	-	-	-	

FIGURE 3: CONNECTION TABLE (3 OF 7)

GMB HR168 Connector Pin	GMB HR168 Signal Name	GMB HR168 Configuration	ZC1 Pin	GMM AM644 Pin	GMM AM644 Configuration	GMM AM644 Signal Name	Use on GMM AM644
<b>CN6: Connector for Asynchronous Serial Line in RS 422</b>							
CN6.1	+5 Vdc	-	34	34	-	+Vdc POW	-
CN6.2	Vopto A	-	-	-	-	-	-
CN6.3	TX- RS422	J3, J4 (*) J7, J8 in 1-2 J5= 2-3 J6=1-2	10	10	Jumpers J1.1 = 1-2 J1.2 = 1-2 J1.3 = 1-2	PDO , TXD RS232 , TXD TTL	-
CN6.4	TX+ RS422						
CN6.5	RX+ RS422	IC10=MAX 483 IC11=MAX 483	9	9		PD1 , RXD RS232 , RXD TTL	-
CN6.6	RX- RS422						
CN6.7	GND	-	20	20	-	GND	-
CN6.8	Vopto B	-	-	-	-	-	-
-	DIR	J10 = L Trasm. Att. J10 = H Trasm. Dis.	11	11	-	PD7 , OC2	-
<b>CN6: Connector for Asynchronous Serial Line in RS 485</b>							
CN6.1	+5 Vdc	-	34	34	-	+Vdc POW	-
CN6.2	Vopto A	-	-	-	-	-	-
CN6.3	-	J3, J4 (*) J7, J8 in 1-2 J5= 1-2 J6=1-2	10	10	Jumpers J1.1 = 1-2 J1.2 = 1-2 J1.3 = 1-2	PDO , TXD RS232 , TXD TTL	-
CN6.4	-						
CN6.5	RXTX+ RS485	IC10=MAX 483 IC11=NM	9	9		PD1 , RXD RS232 , RXD TTL	-
CN6.6	RXTX- RS485						
CN6.7	GND	-	20	20	-	GND	-
CN6.8	Vopto B	-	-	-	-	-	-
-	DIR	J10 = L Trasmissione J10 = H Ricezione	11	11	-	PD7 , OC2	-

FIGURE 4: CONNECTION TABLE (4 OF 7)



GMB HR168 Connector Pin	GMB HR168 Signal Name	GMB HR168 Configuration	ZC1 Pin	GMM AM644 Pin	GMM AM644 Configuration	GMM AM644 Signal Name	Use on GMM AM644		
<b>CN6: Connector for Asynchronous Serial Line in Current Loop</b>									
CN2.1	+5 Vdc	-	34	34	-	+Vdc POW	-		
CN2.2	Vopto A	-	-	-	-	-	-		
CN2.3	TX- C.L.	J3, J4, N.C. J5, Indifferente J6 in 1-2 J7 in 1-2 J8 in 1-2 IC12=HP 4200 IC8=HP 4100	10	10	Jumpers J1.1 = 1-2 J1.2 = 1-2 J1.3 = 1-2	PDO , TXD RS232 , TXD TTL	-		
CN2.4	TX+ C.L.		-	-		-	-	-	
CN2.5	RX+ C.L.		9	9		9	9	PD1 , RXD RS232 , RXD TTL	-
CN2.6	RX- C.L.		20	20		20	20	GND	-
CN2.7	GND	-	-	-	-	-	-		
CN2.8	Vopto B	-	-	-	-	-	-		

FIGURE 5: CONNECTION TABLE (5 OF 7)

Connettore Pin GMB HR168	Nome del Segnale GMB HR168	Configurazione GMB HR168	Pin ZC1	Pin GMM AM644	Configurazione GMM AM644	Nome del Segnale GMM AM644	Utilizzo su GMM AM644
<b>CN7: Connector for Multifunction Signals I/O TTL, A/D, PWM, CAN, etc.</b>							
CN7.1	+5 Vdc	-	34	34	-	+Vdc POW	-
CN7.2	MM PIN 5	-	5	5	-	N.C.	-
CN7.3	MM PIN 14	-	14	14	-	PB.5	-
CN7.4	MM PIN 11	-	11	11	-	INT RTC	-
CN7.5	MM PIN 15	-	15	15	-	PB.6	-
CN7.6	MM PIN 30 , PWM	-	30	30	-	PD.5	-
CN7.7	GND	-	20	20	-	GND	-
CN7.8	MM PIN 33 , A/D	-	33	33	-	PA.0	-
<b>CN5: Connector for Power Supply</b>							
CN5.1	Vac oppure +Vdc	-	-	-	-	-	-
CN5.2	GND	-	20	20	-	GND	-

FIGURE 6: CONNECTION TABLE (6 OF 7)

GMB HR168 Connector Pin	GMB HR168 Signal Name	GMB HR168 Configuration	ZC1 Pin	GMM AM644 Pin	GMM AM644 Configuration	GMM AM644 Signal Name	Use on GMM AM644
<b>CN8: Connector for I2C BUS Line</b>							
CN8.1	+5 Vdc	-	34	34	-	+Vdc POW	+5 Vdc
CN8.2	SCL	-	12	12	-	PC.0 , SCL	I2C BUS
CN8.3	SDA	-	13	13	-	PC.1 , SDA	I2C BUS
CN8.4	GND	-	20	20	-	GND	GND
<b>CN9: Connector for Asynchronous Serial Line in RS 232 (2), USB, ecc.</b>							
CN9.1	+5 Vdc	-	34	34	-	+5 Vdc	-
CN9.2	(+5 Vdc USB)	-	-	-	-	-	-
CN9.3	TX-2	-	39	39	-	TX (2)	-
CN9.4	USB-DL	-	14	14	-	PB.5	-
CN9.5	RX-2	-	40	40	-	RX (2)	-
CN9.6	USB-DH	-	15	15	-	PB.6	-
CN9.7	GND	-	20	20	-	GND	-
CN9.8	GND	-	20	20	-	GND	-

FIGURE 7: CONNECTION TABLE (7 OF 7)